

DIGITUS EV charger for household socket

DK-1P16-A-050-BL
EAN 4016032487791



EV charger, 5m, 230 V, Type F 7/4 to EV Type 2, Adjustable charging power 1,8; 2,3; 2,8; 3,7 kW

The DIGITUS Portable charger DK-1P16-A-050-BL offers a Smart and convenient way to charge E-vehicles. No assembly, no complicated connection. You can charge anywhere from a standard 230 V socket (mains) and Type 2 can be at charging port. The 5 m cable length makes the connection comfortable. With IP55 protection class, carrying to different locations is possible.

Adjustable current between several amperages and fast charging functions

- Rated power : 3,7 kW
- Rated voltage. : 230 V
- Rated current : 8 A/ 10 A/ 12 A / 16 A (adjustable current)

- LCD Display : Showing charging current, voltage, power, charging time, charging status, Internal temperature
- Protection : Over voltage protection, Under voltage protection, Over current protection, Over temperature protection
- Length : 5 m
- Cable type connecting cable: H05 VV-F 3 x 2.5 mm²
- Cable type connecting cable: EV07EE-H 3 x 2.5 mm² + 2 x 0.5 mm²
- Plug : EN 62196-2 Type 2
- Protection class: IP55 (water-jet protected)
- Operating temperature: -20°C+50°C

Package contents

- 1 x Adapter Charger
- 1 X Cable bag
- Quick Installation Guide

| Logistics | | | | | | |
|------------------------------|--------------|-------------|------------|------------|-------------|-----------------|
| | Number (pcs) | Weight (kg) | Depth (cm) | Width (cm) | Height (cm) | cm ³ |
| Packaging Unit Carton | 2 | 13.80 | 37.50 | 36.00 | 22.50 | 30,375.00 |
| Packaging Unit Inside | 1 | 6.90 | 0.00 | 0.00 | 0.00 | 0.00 |
| Packaging Unit Single | 1 | 6.90 | 36.00 | 33.00 | 10.00 | 11,880.00 |
| Net single without Packaging | 1 | 0.00 | 6.00 | 29.00 | 33.00 | 0.00 |

More images:





Safety notes

- It must be installed in a place free from violent vibrations and shocks and placed vertically to facilitate ventilation. It must be installed on non-combustible material such as metal, otherwise there is a risk of fire.
- Use only on mains with residual current circuit breaker.
- It is recommended that the charger undergoes a routine safety check at least once a week.
- Please do not attempt to disassemble, repair or modify the charger yourself. If maintenance or modification is required, please contact a certified electrician / installer. Improper operation may result in damage to the device.
- Do not bring any flammable, explosive or combustible materials, chemicals, flammable vapors or other dangerous goods near the charging station, otherwise there is a risk of fire.
- Please keep the charging adapter clean and dry and wipe it with a clean, dry cloth if it becomes dirty. Do not touch the charging station with your hand when it is charged.
- It is strictly forbidden for children or persons with reduced capacity to approach the charger in order to avoid injury.
- Forced charging is strictly prohibited if the electric vehicle breaks down.
- The electric vehicle may only be charged when the engine is switched off and at a standstill. Do not charge in rain or thunderstorms.
- It is strictly forbidden to use the charger if the charging adapter or the charging cables are defective, cracked, worn or broken or if the charging cables are exposed. Please contact the supplier in good time if you discover such defects.
- You should charge the device carefully during rain or thunderstorms.
- Do not charge if the socket is damaged, rusted, cracked or loosely connected.
- Before charging, make sure that the mains plug and socket are compatible.
- Do not use the appliance in extreme temperatures outside the normal operating range.
- The appliance must be earthed.
- Do not use the appliance with an extension cable or adapter.
- Do not insert fingers into the charging plug.
- If the appliance does not function properly in accordance with the operating instructions, do not use it. Contact your dealer for repair or replacement.
- Do not touch any metal conductors to avoid electric shock.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
 Auf dem Schüffel 3
 Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com