

DIGITUS Adaptador de carregamento universal de 4 portas USB, USB Type-C™

DA-10195
EAN 4016032448105



4-Port USB Charger, 72W, 1xUSB-C (Power Delivery), 5,9,15,20V/3A and 3x USB-A 5V/2.4A, black

O adaptador de carregamento de 4 portas, USB Type-C™ da Digitus® consiste na estação de carregamento universal para todos os seus equipamentos. O adaptador de carregamento C USB (5-20V/3A/60W máx.) com a funcionalidade Power Delivery (PD) 2.0 recarrega Ultrabooks, Notebooks, Tablets, Smartphones, consolas de jogo móveis, etc. de forma rápida e eficiente. Através das três portas de carregamento USB A (total: 5V/2,4A, cada porta fornece até 5V/2,4A máx.) pode carregar qualquer tipo de dispositivo móvel, como, p. ex., Smartphones, Tablets, Power Banks, altifalantes, etc. A capacidade total é de 72W.

Estação de carregamento universal para todos os seus equipamentos (Notebook, Ultrabook, Convertível, Tablet, Smartphone, etc.)

- 1x porta de carregamento USB-C (CC 5-20 V, 3 A, 60W máx.) para carregamento de Notebook, Tablet, Smartphone, etc.
- 3x Porta de carregamento USB-A (total: DC 5V, 2,4A máx., cada porta: CC 5 V, 2,4 A máx.) para carregamento de Tablet, Smartphone, altifalantes, Power Bank, etc.

- Potência total: 72W máx.
- Disponibilização de potência (PD) 2.0
- Entrada: CA 100-240V, 50/60 Hz
- Proteção contra sobretensão, bem como curto-circuito
- Proteção contra sobretensão, bem como sobreaquecimento
- Ficha de alimentação UE
- Comprimento do cabo: 1,20 m
- Ultra compacto – perfeito para viajar, em casa ou na rua
- Dimensões: C 9,0 x L 7,5 x A 2,75 cm
- Peso: 220 g
- Cor: preto
- Style: Charger/Power supply
- Type: Notebook
- USB-C Products: yes

Package contents

- Adaptador de carregamento universal de 4 portas USB, USB Type-C™
- Cabo de rede
- Manual de instruções

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm ³
Packaging Unit Carton	40	16.50	38.00	37.00	30.00	42,180.00
Packaging Unit Inside	1	0.41	14.00	13.60	3.50	666.40
Packaging Unit Single	1	0.41	14.00	13.60	3.50	666.40
Net single without Packaging	1	0.30	9.10	7.50	2.80	0.00

More images:



Safety notes

- Use charging adapters or power supply units in accordance with the instructions in the operating instructions to ensure optimum performance.
- Connect the charging adapter to an easily accessible socket in the voltage range between 100-240 V AC.
- Disconnect the charging adapter from the socket after use.
- Do not use the charging adapter with electronic devices that are outside the specifications of the charging adapter.
- Do not expose the device to rain, moisture, vapors or liquids.
- Do not insert any objects into the device.
- Do not attempt to repair the unit or open the housing without authorization. You risk an electric shock!
- Ensure adequate ventilation to prevent damage due to overheating.
- Dust, moisture, vapors and strong cleaning agents or solvents can cause damage to the device.
- Disconnect the appliance from the power supply and the connected devices before cleaning.
- Clean the device with a dust-free cloth.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
 Auf dem Schüffel 3
 Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com