

DIGITUS Interruptor Gigabit PoE L2 gerido de 8 portas + 2 SFP

DN-95344
EAN 4016032455103



L2 managed Gigabit Ethernet PoE Switch 8-port PoE + 2-port SFP, 86W PoE budget

O interruptor Gigabit PoE L2 gerido DIGITUS® com 8 portas PoE+ e 2 portas SFP Gigabit é ideal para utilizar com diferentes topologias de rede como, por exemplo, em PME. As inúmeras opções de configuração L2 podem aumentar o desempenho e a eficiência da sua rede. O interruptor proporciona a possibilidade de segmentar a rede via VLAN e a funcionalidade QoS garante uma troca de dados sem problemas em aplicações urgentes. Através do Protocolo Spanning Tree ou do Port Trunk, a segurança contra falhas pode ser criada ao estabelecer ligação com outros interruptores. A gestão dos interruptores pode ser realizada através da interface Web, SNMP, SSH ou Telnet.

Funções de Alimentação via Ethernet (PoE) e gestão de rede integrada para ambientes de rede de pequena e média dimensão

- 8 portas 10/100/1000Base-T com suporte PoE
- Uplink SFP Gigabit de 2 Portas
- Saída de corrente PoE 44 ~ 57 V de corrente contínua, no máx. 30 W por porta
- Modo de alimentação de corrente PoE- A, PIN 1/2(+), 3/6(-)
- Configurações VLAN com base na porta / com base em etiqueta / com base em MAC / com base no IP / comando de voz VLAN / mapeamento VLAN / VLAN dupla
- Configurações Trunk, compatibilidade com Rapid Spanning Tree (IEEE802.1d STP, IEEE802.1w RSTP, IEEE802.1s MSTP)
- Suporte QoS
- Filtragem de endereços MAC, filtragem TCP/UDP
- Autenticação Tacacs+ e raio

- Fornece não bloqueamento, avanço de início de fila
- Suporta tomada de pressão e controlo de largura de banda em cada porta
- Tecnologia Store-and-Forward para uma transferência de dados ótima
- Velocidade automática e reconhecimento/ajustamento half/full duplex
- Função Auto-MDI-/MDI-X
- Backplane com 20 Gbps
- Suporta endereços MAC até 8K
- Potência de saída máxima 86 Watt
- Number of ports: 8
- PoE Power budget: 86 W
- PoE standard: IEEE802.3at (PoE+)
- Ethernet speed: Gigabit
- Industrial usage: no
- Installation type: Desktop, 19 inch
- Managed: yes
- Number of ports (Uplink): 2
- Outdoorsuitable: no
- PoE (Power over Ethernet): yes
- Protection against vanadlmis: no
- Uplink port connection: SFP
- VLAN: yes








Package contents

- Interruptor Gigabit PoE L2 gerido de 8 portas
- Peso: 20 g
- Adaptador de corrente
- Acessórios de montagem

Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	10	16.01	34.00	28.00	48.00	45,696.00
Packaging Unit Inside	1	1.60	10.00	16.50	27.50	4,537.50
Packaging Unit Single	1	1.60	3.90	11.50	25.00	1,121.25
Net single without Packaging	1	0.67	3.90	11.50	25.00	0.00

More images:



Safety notes

- This product is intended for indoor use only.
- Read all instructions and follow all warnings and instructions on the device.
- Do not place this appliance on an unstable surface (such as a trolley, stand, table, etc.).
- Do not use this appliance near water.
- Do not place this appliance near or above a radiator.
- The housing is equipped with openings for heat dissipation and ventilation. To prevent overheating during operation, the ventilation openings must not be blocked or covered.
- Do not place the appliance on a soft surface (e.g. bed, sofa, blanket, etc.). This will block the ventilation.
- The appliance must not be installed in a closed environment if adequate ventilation is not guaranteed.
- Do not spray any liquids onto the appliance.
- Disconnect the mains plug before cleaning. Do not use any liquid or foam cleaners.
- Clean the appliance with a damp cloth.
- Connect the device according to the power supply on the rating plate.
- To prevent damage to the appliance, it is important that all appliances are properly earthed.
- Do not place any objects on the power cable and lay it in such a way as to avoid tripping hazards.
- Use a surge protector, a regulator or an uninterruptible power supply (UPS) to protect your system from sudden, temporary and reduced power.
- Secure the system cable and mains cable properly and ensure that no objects are pressing on the cable.
- Do not insert any objects into the appliance through the openings in the housing. There is a risk of a short circuit, which can lead to fire or electric shock.
- Do not attempt to repair the appliance yourself. Always contact an authorized customer service centre.
- If any of the following conditions occur, unplug the appliance and send it to an authorized service centre for repair
- The mains cable, power supply unit or plug for the power supply is damaged or worn;

- Liquid has penetrated the appliance;
- The device has been exposed to rain or water;
- The device has been dropped or the housing has been damaged;
- The function of the device has obviously changed;
- The appliance cannot be operated as described in the operating instructions.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schüffel 3
Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com