

DIGITUS Gigabit Ethernet PoE Injector, Industrial

DN-651141
EAN 4016032486541



Industrial Gigabit PoE Injector Full IEEE802.3af,at,bt Compliant, up to 85 W

The DN-651141 is a single port Mid-spans offer a compact and cost effective, fully IEEE802.3bt compliant solution for remote powering of wireless LAN (WAN) access points, IP Security cameras, VoIP telephone and other low port density installations. The DN-651141 PoE Mid-spans eliminate the need for external power supply and its associated AC/DC power cabling, providing a compact, affordable, safe and reliable power solution over existing Ethernet infrastructure.

Industrial Gigabit PoE Injector, full IEEE802.3af, at, bt Compliant, up to 85 W

- No. of Ports: 1
- Pass Through Data Rates: 10/100/1000Mbps
- Power over Ethernet Output: Pin Assignment and Polarity: Alternative A: V+ (RJ45 Pin3,6), V- (RJ45 Pin 1,2), Alternative B : V+ (RJ45 Pin4,5), V- (RJ45 Pin 7,8), User Port Power: 84W max
- Input Power Requirements: DC Input Voltage: 45 to 56 VDC
- Indicators: System Indicator: DC Power
- User Indicator: Channel Power
- Connectors: Shielded RJ-45, EIA 568A and 568B
- Regulatory Compliance: IEEE802.3af, IEEE802.3at, IEEE802.3bt type3, IEEE802.3bt type4
- Full IEEE802.3af, IEEE802.3at, IEEE802.3bt Compliant
- Up to 85W of Power on 4-pairs
- Auto-detect of IEEE802.3af, IEEE802.3at, IEEE802.3bt PD

- Supports 10/100/1000Base-T applications
- LED indicators power input and PoE output indication
- Distance up to 100 meters
- DC Input 45~56V
- DIN-Rail installation
- Wide operating temperature: -40 ~ +75°
- Environmental Conditions: Operating Ambient Temperature: -40 ~ +75°
- Operating Humidity: 90%, Non-condensing
- Storage Temperature: -40 to 75°
- Storage Humidity: 95%, Non-condensing
- Dimension (W x D x H): 103 x 78 x 32 mm
- Weight: 295g

Attributes

- Industrial usage: no
- Managed: no
- Outdoorsuitable: no
- PoE (Power over Ethernet): no
- Protection against vanadism: no
- VLAN: no

Package contents

- Industrial Gigabit Ultra Power over Ethernet Injector x 1
- User's Manual x 1
- DIN Rail Kit x 1

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm ³
Packaging Unit Carton	36	11.93	25.50	39.20	49.00	48,980.40
Packaging Unit Inside	1	0.33	0.00	0.00	0.00	0.00
Packaging Unit Single	1	0.33	9.50	18.80	24.00	4,286.40
Net single without Packaging	1	0.00	14.50	5.40	16.50	0.00

More images:



Safety notes

- This product is intended for indoor use only.
- Read all instructions and follow all warnings and instructions on the device.
- Do not place this appliance on an unstable surface (such as a trolley, stand, table, etc.).
- Do not use this appliance near water.
- Do not place this appliance near or above a radiator.
- The housing is equipped with openings for heat dissipation and ventilation. To prevent overheating during operation, the ventilation openings must not be blocked or covered.
- Do not place the appliance on a soft surface (e.g. bed, sofa, blanket, etc.). This will block the ventilation.
- The appliance must not be installed in a closed environment if adequate ventilation is not guaranteed.
- Do not spray any liquids onto the appliance.
- Disconnect the mains plug before cleaning. Do not use any liquid or foam cleaners.
- Clean the appliance with a damp cloth.
- Connect the device according to the power supply on the rating plate.
- To prevent damage to the appliance, it is important that all appliances are properly earthed.
- Do not place any objects on the power cable and lay it in such a way as to avoid tripping hazards.
- Use a surge protector, a regulator or an uninterruptible power supply (UPS) to protect your system from sudden, temporary and reduced power.
- Secure the system cable and mains cable properly and ensure that no objects are pressing on the cable.
- Do not insert any objects into the appliance through the openings in the housing. There is a risk of a short circuit, which can lead to fire or electric shock.
- Do not attempt to repair the appliance yourself. Always contact an authorized customer service centre.
- If any of the following conditions occur, unplug the appliance and return it to an authorized service centre for repair
- The mains cable, power supply unit or plug for the power supply is damaged or worn;
- Liquid has penetrated the appliance;
- The device has been exposed to rain or water;
- The device has been dropped or the housing has been damaged;
- The function of the device has obviously changed;
- The appliance cannot be operated as described in the operating instructions.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
 Auf dem Schüffel 3
 Lüdenscheid, Germany
<https://www.assmann.com>
 info@assmann.com