

# DIGITUS VGA Switch 2 PCs, 1 Monitor

DS-44100-1

EAN 4016032323532



## VGA Switch, 2 inputs, 1 output 250MHz, incl. power supply, DC9V, 300mA, 1080p

The VGA Video Switch is the excellent solution for connecting and switching between multiple PCs to one display. It eliminates the hassle of having to swap out connections to the display and allows easy selecting of the video source by the push of a button. In addition, the switch has an audio function, whereby video and audio signals can be transmitted simultaneously.

### Easy and convenient video source selection by push button

- Ideal for school classes, workshops, training rooms, etc.
- 2 inputs (PC), 1 output (monitor, beamer, etc.)
- Max. resolution: 1920x1080p @60Hz
- Video bandwidth 250MHz
- Video input connections: HDSUB15/female

- Video output connections: HDSUB15/female
- Audio input connection: 1 x 3.5 mm audio jack
- Audio output connections: 2 x 3.5 mm audio jack

### Attributes

- HDTV Resolution max.: 1920 x 1080 Pixel, 60Hz
- HDTV Standard: Full HD
- Number of ports: 2
- Signal input: VGA
- Signal output: VGA

### Package contents

- VGA Switch 250 MHz, 2 Inputs, 1 Output
- Power supply
- Manual

## Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm <sup>3</sup>
Packaging Unit Carton	10	8.30	32.00	28.00	33.00	29.57
Packaging Unit Inside	1	0.83	6.00	25.50	15.00	2.30
Packaging Unit Single	1	0.83	6.00	25.50	15.00	2.30
Net single without Packaging	0	0.57	9.00	13.80	4.00	496.80

## More images:



**Safety notes**

- If the device is powered by a plug-in power supply, ensure that the power adapter is connected correctly and meets the specified requirements (e.g. voltage and current).
- Only use certified CAT5e or CAT6 cables to ensure stable signal transmission.
- For particularly long cable runs or in environments prone to interference, it is recommended to use shielded network cables.
- Make sure that all connections are tight and secure to avoid loose contacts that could affect the signal quality. Make sure that the HDMI and Ethernet connections are connected correctly.
- Make sure that the CAT cable is not laid near high-voltage power lines or other strong sources of electromagnetic interference to avoid signal interference.
- Only operate the device within the specified temperature range.
- Do not use the device outdoors or in damp or wet environments
- Check all connections and cables regularly for wear or damage. Cables and connections can wear out, especially with frequent use or long installations, which can lead to poor signal quality or system failure.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schüffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)