

DIGITUS Socket strip with aluminum profile and surge protection, integrated line filter, 7-way Italian socket, 2 m cable Italian plug

DN-95412-IT
EAN 4016032483885



Aluminium PDU, 7x Italian outlet, frequency filter 16A, 4000W, 250VAC 50/60Hz, 2m

The DIGITUS® socket strips are the perfect solution for your network or server cabinet. With regard to current distribution, the PDU fulfills the requirements of many applications in IT, network technology, laboratories and also home use. The socket strip can be mounted vertically in the cabinet. An integrated line filter and surge protection protect the connected consumers against disruptions from the grid. It is possible, depending on the type of cabinet, to mount the power strip with the taps facing right or left.

Safe and professional current supply in the network / server cabinet range

- Integrated line filter

- Integrated surge protection: Nominal discharge current (In) – 10 kA
- Vertical rack installation
- Socket rotation: 35°
- Housing: Aluminum
- Plastic components made of ABS UL-94V-0
- Input: Italian plug, 230 Vac / 16 A
- Output: Italian sockets, max. 16 A per output
- Cable: H05VV-F 3G 1.5 mm², length: 2 m
- Dimensions: 620 x 45 x 45 mm (HxWxD)



Package contents


- Scope of delivery: 1 socket strip, 2 mounting brackets; 1 safety instructions

Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm ³
Packaging Unit Carton	10	14.82	26.50	66.50	31.50	55,510.90
Packaging Unit Inside	1	1.48	0.00	0.00	0.00	0.00
Packaging Unit Single	1	1.48	12.00	65.00	5.80	4.52
Net single without Packaging	0	0.11	4.50	62.00	4.45	1,241.55

More images:



**Safety notes**

- This product is not intended for unsupervised use by children or persons under their care!
- Prevent higher humidity or temperatures than those specified in the data sheet - Avoid moisture, dust or vapors, solvents, flammable gases.
- Multiple sockets are not designed for permanent use with heavy loads!
- Multiple sockets must not be cascaded (avoid stringing together several multiple sockets).
- The maximum connected load must not be exceeded.
- Defective multiple sockets must be taken out of service immediately and disposed of in an environmentally friendly manner.
- In the event of a fault, take the product out of operation and contact a qualified electrician.
- Do not open the product.
- Disconnect the product from the power supply before cleaning. Do not use any aggressive or abrasive cleaning agents for cleaning.
- The ingress of liquids can lead to a short circuit.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schüffel 3
Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com