

# DIGITUS 2.5"/3.5" USB 3.0 Dual SATA HDD Docking Station

DA-71540-1  
EAN 4016032458791



### SATA Docking Station USB3.0, 2-port, 2.5"/3.5" SSD/HDD, clone function

The DIGITUS USB 3.0 Dual SATA HDD Docking Station reads and writes 2.5" and 3.5" HDD SATA hard drives simultaneously without the need for a PC or notebook. The USB 3.0 technology enables data transfer, backups, and conversions at transfer speeds of up to 5 Gbps. The DIGITUS USB 3.0 Dual SATA HDD Docking Station is downward compatible to USB 1.1, meaning that you can work with older SATA hard drives with no problem. The clone function can also be used to transfer data 1:1 to another hard drive. Start the process at the touch of a button and follow the progress using the LED display. The perfect solution for backups, data archiving, and hard drive cloning.

### Backups, data archiving, and clone function with SuperSpeed USB 3.0

- Accommodates two 3.5 or 2.5 SATA hard drives, plug-in unit, data can be transferred between 2.5 and 3.5 SATA hard drives

- Clone function
- Two hard drives can be read or written simultaneously
- Supports SuperSpeed USB 3.0 up to 5 Gbps, high speed USB 2.0 up to 480 Mbps and full speed USB 1.1 at 12 Mbps
- Supports hotswapping of connected devices
- Supports SATA III (6 Gbps) / SATA II (3 Gbps) / SATA I (1.5 Gbps)
- LED display for monitoring the cloning process
- Includes 12 V DC /2,5 A power supply unit
- Includes data cable (USB 3.0, type B)
- Hard disc capacity: 8 TB per slot / 16 TB total

### Package contents

- 2.5"/3.5" USB 3.0 Dual SATA HDD Docking Station
- USB 3.0 cable
- 12V/2.5A power supply unit
- Manual

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm <sup>3</sup>
Packaging Unit Carton	20	11.40	50.00	34.00	49.00	83,300.00
Packaging Unit Inside	1	0.57	23.50	9.30	16.00	3,496.80
Packaging Unit Single	1	0.57	12.90	7.20	9.60	891.65
Net single without Packaging	1	0.46	12.90	7.20	9.60	891.65

### More images:



**Safety notes**

- Overloading can lead to overheating and damage to the appliance or the connected peripherals.
- If necessary, use an external power supply to ensure stable performance.
- If devices such as external hard disks or printers that require a high power consumption are connected, the device should be used with an external power supply. Otherwise, the device could be overloaded or functional problems could occur.
- Do not expose the device to rain, moisture, vapors or liquids.
- Do not insert any objects into the device.
- Do not attempt to repair the unit or open the housing without authorization. You risk an electric shock!
- Ensure adequate ventilation to prevent damage due to overheating.
- Dust, moisture, vapors and strong cleaning agents or solvents can cause damage to the device.
- Disconnect the appliance from the power supply and the connected devices before cleaning.
- Clean the device with a dust-free cloth.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schüffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)