

# DIGITUS USB Charger 1x USB-A / 1x USB-C, 30W

DA-10062  
EAN 4016032482710



**USB Charger 1x USB-A / 1x USB-C 30W Dual Port, 1x 2,4A, 1x 3A, QC3.0**

The Dual Port Charging Adapter from DIGITUS® is suitable for USB devices such as smartphones or tablets and provides an output of 30W via the USB-C port or 18W via the USB A port. 2 USB devices can be charged with 15W each at the same time. The integrated short circuit, surge and excess current protection provides added security. Furthermore, the integrated excess heat protection prevents potential overloads and damages to the charger or connected devices.

**High-performance wall charger with an output of up to 18W for USB-C™ and 12W for USB A devices**

- Double connection: 1x USB Type-C™ (PD) and 1x USB A (QC)
- Compatible with smartphones and tablets from Apple, Huawei, XIAOMI, Google, Samsung
- Input voltage: 100 - 240 V AC, 50/60 Hz
- Output voltage USB-C, PD: 5V/3A, 9V/3A, 12V/2,5A, 15V/2A, 20V/1.5A (30W max.)

- Output voltage USB-A QC3.0: 5V/3A, 9V/2A, 12V/1.5A (18W max.)
- Note: When both ports are connected, they share a power output of at most 15W (5V, 3A) and do not support any PD and QC fast charging.
- Supports Power Delivery 3.0 with 18W charging capacity
- Surge protection / excess current protection / overload protection / short circuit protection
- Protection against overheating with automatic switch-off and recovery (auto-recovery)
- Housing: Fire-resistant material
- Dimensions: L 29 x W 35 x H 84 mm
- Color: White
- Weight: 61g
- Style: Charger/Power supply

**Package contents**

- 1x USB Charger 1x USB-A / 1x USB-C
- QIG (Quick Installation Guide)

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	0	0.00	0.00	0.00	0.00	0.00
Packaging Unit Inside	0	0.00	0.00	0.00	0.00	0.00
Packaging Unit Single	0	0.00	0.00	0.00	0.00	0.00
Net single without Packaging	0	0.00	0.00	0.00	0.00	56.88

More images:

