

DIGITUS HDMI Adapter, HDMI to DVI-I

DB-330505-000-S EAN 4016032298700





HDMI adapter, type A - DVI-I(24+5) M/F, comp. to former HDMI 1.3,

This adapter is suitable for connecting HDMI Type A cables to devices or cables with a DVI-I plug. It supports digital or analog signal transmission. The adapter works bi-directionally, which means it can adapt in both directions.

Dual link adapter from HDMI to DVI - supports digital and analog signals

- Supports up to 1080p with 60 Hz
- Supports DVI 24+5 and DVI 24+1

Attributes

- HDTV rezolucija maks.: 1920 x 1200 piksela, 60 Hz
- HDTV-norma: Full HD
- Kabel u boji: crni
- Kapice: ukalupljeno
- Konektor 1: HDMI tip A, utikač
 Konektor 2: DVI-I, (24+5), priključak
- Površina konektora: poniklano
- AOC aktivni optički kabel: Ne
- oklop: jednostruki oklop

Package contents

1 x HDMI Adapter, HDMI to DVI-I

| Logistics | | | | | | |
|------------------------------|-----------------|----------------|---------------|---------------|----------------|--------|
| | Number (pcs) | Weight (kg) | Depth (cm) | Width (cm) | Height (cm) | cm³ |
| Packaging Unit Carton | 10 | 0.80 | 37.50 | 11.50 | 16.00 | 6.90 |
| Packaging Unit Inside | 10 | 0.80 | 37.50 | 11.50 | 16.00 | 6.90 |
| Packaging Unit Single | 1 | 0.08 | 3.50 | 10.00 | 13.50 | 472.50 |
| Net single without Packaging | 0 | 0.00 | 3.50 | 10.00 | 13.50 | 472.50 |

More images:















Safety notes

- When plugging and unplugging the cable, only grasp the plug and do not pull directly on the cable.
- Cables must not be kinked sharply or bent at tight angles, as this can damage the inner wires and lead to failures.
- · Make sure that the cables are not under tensile load, as this can damage the insulation and the wires inside the cable.
- Ensure that cables are not laid in areas where they can be easily damaged mechanically.
- Cables should not be used in environments with extremely high or very low temperatures. Observe the product information on the maximum
 operating temperature of the cable
- Check cables regularly for visible damage such as cracks, kinks or signs of wear. Defective cables should be replaced immediately to avoid failures, short circuits or even electric shocks.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH Auf dem Schüffel 3 Lüdenscheid, Germany https://www.assmann.com info@assmann.com