

DIGITUS Universal Notebook Power Adapter, 90W

DA-10190 EAN 4016032390503





The DIGITUS Universal Notebook Power Adapter is a super slim and compact replacement for defective or lost original power adapters. It is also ideal as a secondary power adapter for the office, for travel or at home. It offers 11 charging adapters for virtually every notebook from the most popular brands such as Acer, Asus, Samsung, Sony, HP, Toshiba, Lenovo, Fujitsu, IBM, Compaq, NEC, etc. The required output voltage is automatically controlled by the selected matching charging adapter. It also has an additional USB charging port for charging mobile devices such as smartphones, tablets, cameras, etc. Notebooks, as well as the power adapter itself, are protected against short circuit, overheating, overvoltage and overcurrent.

Super slim and compact replacement for defective or lost original power adapters and also perfectly suitable as a secondary power adapter for travel, in the office or at home.

- Suitable for notebooks from the most popular brands such as Acer, Dell, Asus, Samsung, Sony, HP, Toshiba, Lenovo, Fujitsu, Compaq, NEC, etc.
- 11 different adapters for virtually every notebook
- Ultra slim, compact and lightweight spare or secondary power adapter - perfect for travel, in the office or at home
- Easy and safe selection of the output voltage through the inserted adapter plug



- Additional USB charging port for charging mobile devices
- Input voltage (AC): 100-240V suitable for worldwide use in conjunction with a country-specific adapter
- Output voltage (DC): 12-24V
- USB charging port: 5V/2.0A
- Max. output power: 90W
- Max. output current: 6.0A
- Protection against short circuit, overheating, overvoltage and overcurrent
- Cable length: 1.40 m (power cord), 1.00 m (notebook connection)
- Power Cord, Euro C7
- LED activity indicator
- Efficient and energy-saving design energy efficiency level VI
- Dimensions: L 11.3 x B 7.0 x H 1.7 cm
- Weight: 235 g
- Color: black

Attributes

Vrsta: Punjač/napajanje

Package contents

- Universal Notebook Power Adapter, 90W
- 11 charging adapters
- · Power Cord, Euro C7
- User manual

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	20	11.70	27.80	42.30	57.30	67,381.40
Packaging Unit Inside	1	0.59	17.00	22.00	3.50	1.31
Packaging Unit Single	1	0.59	17.00	22.00	3.50	1.31
Net single without Packaging	0	0.24	17.00	70.00	114.00	135.66



More images:









Safety notes

- Use charging adapters or power supply units in accordance with the instructions in the operating instructions to ensure optimum performance.
- Connect the charging adapter to an easily accessible socket in the voltage range between 100-240 V AC.
- Disconnect the charging adapter from the socket after use.
- Do not use the charging adapter with electronic devices that are outside the specifications of the charging adapter.
- Do not expose the device to rain, moisture, vapors or liquids.
- Do not insert any objects into the device.
- Do not attempt to repair the unit or open the housing without authorization. You risk an electric shock!
- Ensure adequate ventilation to prevent damage due to overheating.
- Dust, moisture, vapors and strong cleaning agents or solvents can cause damage to the device.
- Disconnect the appliance from the power supply and the connected devices before cleaning.
- Clean the device with a dust-free cloth.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH Auf dem Schüffel 3 Lüdenscheid, Germany https://www.assmann.com info@assmann.com