

DIGITUS Mobile charging cabinet for 30 notebooks / tablets up to 15.6 inch, data synchronization, UV-C, USB-A

DN-45005
EAN 4016032486152



Charging trolley, UV-C, data synchronization 30 charge bases, 15.6", black

The mobile charging cabinet from DIGITUS® is the ideal and compact solution for storing and charging your portable devices such as notebooks and tablets. Mobile charging cabinets are frequently used in public facilities such as schools in order to store devices securely at a central location while charging them at the same time. The cabinet includes 3 rows with 10 charging stations each, all of which have their own USB connection on the front. The devices can also be connected with installed socket strips (3 x 10 safety sockets) at the back. Thanks to ample cable feedthroughs and excess cable storage, optimal cable management is guaranteed. Installed ventilators (3 x 24 V) combined with ventilation slits ensure active cooling of the cabinet. Installed UV-C lamps ensure sterile conditions and thus environmentally friendly, enhanced hygiene. For centralized synchronization of data, a device can be connected to the external USB port.

The ideal solution for sterile storage and charging your portable devices via USB-A connections. Including option for data synchronization.

- UV-C lamps for improved hygiene
- Option for data synchronization
- Double Folding Front and Back Door
- Pressure lock system with swiveling lever handle on the front and back door, lockable
- 180° door opening angle
- 2-point locking (rod lock)
- Incl. 4 rollers (2 lockable)

- Including handles for better mobility (enclosed)
- Product dimensions (H x W x D) in mm: 1260 x 824 x 650 mm
- Safety plug socket (AC) with switch on the side
- C20 connection on the side
- Incl. RCD 30 mA (residual current operated device)
- Delivery is completely assembled
- Depth of inner tray: 415 mm (suitable for up to 15,6" devices)
- Completely assembled upon delivery
- Casters can be dismantled if necessary
- USB-A Port Output: 10W (5 V 2.1A) per port; 300W max.
- Temperature control: Fans start automatically when the internal temperature exceeds 40 °C
- Boja: crna, RAL 9005
- Suitable for display size: 39,6 cm (15,6")
- Number of Devices: 30
- USB connection (charging): USB A
- Additional connection (charging): Safety outlets
- UV-C disinfection: Da
- Data synchronisation function: Da
- Type: Trolley
- Locking type: mechanical

Package contents

- Mobile charging cabinet
- 2 x handle (for installation on outside) including mounting material
- Power cable, 2 m
- User manual
- 4 x keys

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	1	128.00	69.00	77.00	126.00	669.44
Packaging Unit Inside	1	128.00	69.00	77.00	126.00	669.44
Packaging Unit Single	1	128.00	69.00	77.00	126.00	669.44
Net single without Packaging	0	96.00	65.00	82.40	126.00	674.86

More images:



Safety notes

- The product may only be operated on sockets that are protected by a residual current circuit breaker.
- The electrical connection of the product must be made directly to a permanently installed socket.
- The use of multiple sockets or extension cables is not permitted.
- The connection cable must be undamaged. A cable with kinks, crushing or cracks must be replaced immediately.
- Before connecting electrical devices to the product, ensure that the device to be connected, including its connection cable, is in a fault-free and damage-free condition.
- Always insert the plug fully into the socket. It may only be disconnected by pulling on the plug itself - never pull on the cable.
- When operating doors or flaps, care must be taken to ensure that the connecting cables of electrical devices are not crushed or damaged
- Use only in dust and moisture-protected indoor areas
- Prevent higher humidity or temperatures than those specified in the data sheet - Avoid moisture, dust or vapors, solvents, flammable gases.
- Avoid moisture, dust or vapors, solvents, flammable gases.
- The appliance may only be dismantled and transported if the mains plug has been disconnected beforehand.
- Only connect the charging system to an earthed and easily accessible socket.
- Safety must be assessed by a qualified electrician.
- The sockets may only be used with the devices intended for this purpose, for example:
 - Chargers for rechargeable batteries and hand-held devices
 - Smartphones or tablets (mobile devices)
 - Laptops / Notebooks / UltraBooks (mobile computers)
 - Mobile batteries / PowerBanks
- Please ensure that the maximum total output specified on the rating plate is not exceeded.
- Please also ensure that no liquids enter the electrical equipment of the cabinet.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
 Auf dem Schüffel 3
 Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com